GRAS 45BB-4

KEMAR Head & Torso for Sound Quality Recording, 2-Ch CCP





Connection: Constant Current Power (0 V/CCP)
Channel(s): 2
ANSI: S3.36
ITU-T Rec. P.57 Type 3.3
based on ITU-T Rec. P.58

The 45BB-4 KEMAR Head and Torso with TEDS for Sound Quality Recording is an acoustic research tool with built-in 1/2" microphones for realistic sound quality testing and recordings. It is easy to replace the 1/2" microphones with 1/4" microphones if preferred. Its LEMO equivalent is GRAS 45BB-3 KEMAR Head & Torso for Sound Quality Recording, 2-Ch LEMO.



Technology

Introduction

The KEMAR head and torso simulator was introduced by Knowles in 1972 and quickly became the industry standard for hearing-aid manufacturers and research audiologists (visit KEMAR.us to read the full story). It is based on worldwide average human male and female head and torso dimensions. It meets the requirements of ANSI \$3.36/ASA58-2012 and IEC 60318-7:2011.

The GRAS 45BB KEMAR Head and Torso has the same dimensions and acoustical properties as the original KEMAR, but has been developed further by GRAS to meet the industry's demand for realistic measurements of hearing aids, headphones and headsets. It provides acoustic diffraction similar to that encountered around the median human head and torso, both in the proximity and in the far field.

As all the preconfigured 45BB KEMARs consist of the same basic 45BB KEMAR Non-configured, plus a set of application specific accessories, the full information about a given KEMAR configuration is obtained by combining the information about the 45BB KEMAR Non-configured and the information for a given configured version as found in the present text. Read about the non-configured KEMAR here.

TEDS Compatibility

All CCP-based KEMAR configurations are IEEE 1451.4 TEDS v. 1.0 compliant. If your measurement platform supports Transducer Electronic Data Sheets (TEDS), you will be able to read and write data like properties and calibration data.

Design

The 45BB-4 is a KEMAR head and torso for 2-channel sound quality recording, with prepolarized ½" pressure microphones.

It is delivered fully configured, individually calibrated and ready for use. In addition to a system calibration certificate, a USB flash memory with simulation data is included.

The main configuration specific components of the 45BB-4 are the GRAS 40A0 ½" pressure microphones and the KB0090/KB0091 large tapered (VA-style) pinnae.

The 40A0 1/2" Prepolarized Pressure Microphones

The 40A0 is an IEC 61094 WS2P ½" prepolarized pressure microphone with rear-venting.

It is a high-precision condenser microphone made according to IEC 61094-4. It is extremely robust and reliable and can measure sound pressure levels up to 160 dB within 3.15 Hz to 20 kHz.

Read more about 40A0 here.

The KB0090/KB0091 Pinna

The KB0090 and KB0091 are large VA-style pinnae. The hardness is 55 Shore 00 and they comply with IEC 60318-7.

Other accessories for this configuration are listed in the Ordering Info tab.

Performance and warranty

KEMAR is made of components from our standard portfolio and are all manufactured of high-quality material and branded parts that were chosen and processed to ensure life-long stability and robustness. This, enables us to offer 2 years warranty against defective materials and workmanship.

Exceptions: Microphones included in KEMAR as for these our normal 5 year warranty apply. The warranty period for cables is 6 months.



Specifications

| Connector type | | BNC |
|---|-------------|------------------------|
| Set sensitivity @ 250 Hz (±2 dB) | mV/Pa | 12.5 |
| Set sensitivity @ 250 Hz (±2 dB) | dB re 1V/Pa | -38.5 |
| Theoretical dynamic range lower limit with GRAS preamplifier | dB(A) | 25 |
| Theoretical dynamic range upper limit with GRAS preamplifier @ +28 V / ±14 V power supply | dB | 150 |
| Temperature range, operation | °C / °F | -30 to 60 / -22 to 140 |
| Temperature range, storage | °C / °F | -40 to 65 / -40 to 149 |
| Humidity range non condensing | % RH | 0 to 95% |
| ANSI standard | | S3.36 |
| Weight | g / oz | 11.45 k / 404 |

GRAS Sound & Vibration reserves the right to change specifications and accessories without notice.



Included

| GRAS 45BB | KEMAR Head & Torso, non-configured |
|----------------------|---|
| <u>GRAS KB0090</u> | KEMAR Large Right Ear 55 Shore 00 (VA/SQ) |
| GRAS KB0091 | KEMAR Large Left Ear 55 Shore 00 (VA/SQ) |
| GRAS RA0241 | Holder for short 1/2" microphone Kit for KEMAR (2 pcs) |
| <u>GRAS AA0018-S</u> | Microdot-BNC Cable, 35 cm (2 pcs) |
| GRAS AA0035 | BNC-BNC Cable, 3 m (2 pcs) |
| GRAS 46A0-S2 | 1/2" Pressure Microphone set, prepolarized with very short preamplifier (2 pcs) |

Optional items

Power Modules for Pre-polarized Ear Simulators and Microphones

| GRAS 12AL | 1-Channel CCP Power Module with A-weighting filter |
|-----------|--|
| GRAS 12AQ | 2-Channel Universal Power Module with signal conditioning and PC interface |

For Ear Simulator Calibration

| GRAS 42AP | Intelligent Pistonphone (250 Hz or 251.2 Hz, 114 dB +/- 0.05 dB) |
|-------------|--|
| GRAS 42AA | Pistonphone (250 Hz, 114 dB +/- 0.08 dB) |
| GRAS RA0157 | 1/2" Calibration Adapter for KEMAR Pinna |

Pinna Simulators

| GRAS KB0060- S1 | KEMAR Small Right Pinna for SQ, 55 Shore 00 |
|--------------------|---|
| GRAS KB0061- S1 | KEMAR Small Left Pinna for SQ, 55 Shore 00 |
| GRAS KB1060- S1 | KEMAR Small Right Pinna for SQ, 35 Shore 00 |
| GRAS KB1061-S1 | KEMAR Small Left Pinna for SQ, 35 Shore 00 |
| GRAS KB0060 | KEMAR Small Right Ear 55 Shore 00 |



Ordering Info

| <u>GRAS KB0061</u> | KEMAR Small Left Ear 55 Shore 00 |
|--------------------|--|
| GRAS KB0065 | KEMAR Large Right Ear 55 Shore 00 |
| <u>GRAS KB0066</u> | KEMAR Large Left Ear 55 Shore 00 |
| GRAS KB1060 | KEMAR Small Right Ear, 35 Shore 00 |
| GRAS KB1061 | KEMAR Small Left Ear 35 Shore 00 |
| GRAS KB1065 | KEMAR Large Right Ear 35 Shore 00 |
| <u>GRAS KB1066</u> | KEMAR Large Left Ear 35 Shore 00 |
| <u>GRAS KB0090</u> | KEMAR Large Right Ear (VA-Style/SQ) 55 Shore 00 |
| <u>GRAS KB0091</u> | KEMAR Large Left Ear (VA-Style/SQ) 55 Shore 00 |
| <u>GRAS KB1090</u> | KEMAR Large Right Ear (VA-Style) 35 Shore 00 |
| GRAS KB1091 | KEMAR Large Left Ear (VA-Style) 35 Shore 00 |
| GRAS KB5000 | KEMAR Large Right Anthropometric Pinna 35 Shore 00 |
| GRAS KB5001 | KEMAR Large Left Anthropometric Pinna 35 Shore 00 |

Ear Mould Simulators

| <u>GRAS KB0110</u> | Ear Mould Simulator for 2 mm Inner diameter tubing |
|--------------------|--|
| GRAS KB0111 | Ear Mould Simulator for 3 mm Inner diameter tubing |

Ear Canal Extension and Microphone Holder Kits (kits with 2 pcs and 0-rings)

| GRAS RA0237 | Straight Ear Canal Extension Kit for KEMAR |
|-------------|--|
| GRAS RA0238 | VA-tapered Ear Canal Extension Kit for KEMAR |
| GRAS RA0239 | Ear canal Extension Kit w. silicone lining for KEMAR |
| GRAS RA0240 | Holder for long 1/2" microphone Kit for KEMAR |
| GRAS RA0241 | Holder for short 1/2" microphone Kit for KEMAR |
| GRAS RA0243 | Holder for 1/2" microphone Kit for KEMAR |
| GRAS RA0244 | O-ring kit for KEMAR, 2 pcs. |
| GRAS RA0249 | Straight Ear Canal Extension Kit for KEMAR, made of POM, for binaural hearing aid test |



Ordering Info

| GR | | |
|----|--|--|
| | | |

Tapered Ear Canal Extension Kit for KEMAR, made of POM, for binaural hearing aid test

KEMAR Retrofit Kit for Anthropometric Concha and Canal Pinna

| <u>GRAS RA0311</u> | KEMAR Retrofit Kit for Anthropometric Concha and Canal Pinna. The Kit includes Ear Simulator Holder, 2 finger screws and a 3 mm Allen Key. |
|--------------------|--|
| | |

Extension Cables

| GRAS AA0034 | BNC-BNC Cable, 2 m |
|--------------------|---------------------|
| <u>GRAS AA0035</u> | BNC-BNC Cable, 3 m |
| GRAS AA0036 | BNC-BNC Cable, 5 m |
| GRAS AA0037 | BNC-BNC Cable, 10 m |

Flight Case

| GRAS KM0094 | PELI Case for KEMAR |
|-------------|---------------------|

Simulation Model of KEMAR

| GRAS KB3000 | Simulation Model of KEMAR with large pinnae |
|-------------|---|
| GRAS KB3001 | Simulation Model of KEMAR with small pinnae |

Stand for KEMAR

| GRAS AL0026 |
|-------------|
|-------------|

Miscellaneous

| GRAS KB0000 | KEMAR Handbook |
|-------------|-------------------|
| GRAS KB0010 | T-Shirt for KEMAR |

GRAS Sound & Vibration reserves the right to change accessories without notice.



GRAS Worldwide

Subsidiaries and distributors in more than 40 countries

HEAD OFFICE, DENMARK

GRAS SOUND & VIBRATION

Skovlytoften 33 2840 Holte Denmark Tel: +45 4566 4046 www.GRASacoustics.com gras@grasacoustics.com

USA

GRAS SOUND & VIBRATION

9290 SW Nimbus Avenue Beaverton, OR 97008 Tel: 503-627-0832 Toll Free: 800-231-7350 www.GRASacoustics.com sales-usa@grasacoustics.com

uĸ

GRAS SOUND & VIBRATION

Unit 115, Gibson House, Ermine Business Park, Huntingdon, Cambridgeshire, PE29 6XU Tel: +44 (0) 7762 584 202 www.GRASacoustics.com sales-uk@grasacoustics.com

ANIHO

GRAS SOUND & VIBRATION

Room 315, RuiBo Center(T1) Lane683, Shenhong Rd, Minhang District, Shanghai, China, 201107 Tel: +86 21 64203370 www.GRASacoustics.cn cnsales@grasacoustics.com



About GRAS Sound & Vibration

GRAS is a worldwide leader in the sound and vibration industry. We develop and manufacture state-of-the-art measurement microphones and related equipment for industries where acoustic measuring accuracy and repeatability are of the utmost importance. This includes applications and solutions for customers within the fields of aerospace, automotive, audiology, consumer electronics and other highly demanding industries. GRAS microphones are designed to live up to the high quality, durability and accuracy that our customers have come to expect, trust and require.

GRAS Sound & Vibration is represented through subsidiaries and distributors in more than 40 countries and is part of Axiometrix Solutions, a leading test solutions provider comprised of globally recognized measurement brands. Read more at www.grasacoustics.com

